Rated current [A]	125
Short-time withstand current [A]	4 200
Rated voltage Ui [V]	500
Tightening torque [Nm]	2,5 (6 ÷ 35 mm <sup>2</sup> )
Tightening torque [Nm]	2 (1,5 ÷ 16 mm <sup>2</sup> )
Tool	Inbus number 4 / PH 2
Assembly method	TH 35 / on the plate
Number of clamping points per level	15 (for 1 pole)
Number of levels	2
Number of poles	2
End cover plate required	NO
Testing	EN 60947-7-1
Dimensions [mm] (width / height / length)	182 / 50 / 44
Weight [g]	280
Packing [pcs]	1
Note	The distribution blocks are intended for copper conductors only. Flexible conductors must be provided with a ferrule.
Conductor cross section	
Conductor cross-section – Input [mm <sup>2</sup> ]	1 x 6 ÷ 35 (flexible conductor with ferrule max. 25)
Conductor cross-section – Output [mm <sup>2</sup> ]	3 x 4 ÷ 25 (flexible conductor with ferrule max. 16)
Conductor cross-section – Output [mm <sup>2</sup> ]	11 x 1,5 ÷ 16 (flexible conductor with ferrule max. 10)

